



## Leading - edge Technology

- ▶ Pure sine wave inverter
- ▶ Built-in MPPT solar charge controller
- ▶ Selectable input voltage range for home appliances and personal computers
- ▶ Selectable charging current based on application
- ▶ Configurable AC/Solar input priority via LCD setting
- ▶ Compatible to mains voltage or generator power
- ▶ Auto restart while AC is recovering
- ▶ Overload and short circuit protection
- ▶ Smart battery charger design for optimized battery performance
- ▶ Cold start function
- ▶ Parallel operation with up to 6 units only available for 4KVA/5KVA
- ▶ Optional Remote Control Panel available

## GROWATT NEW ENERGY TECHNOLOGY Co.,LTD

A: No.28 Guanghui Road, Longteng Community, Shiyan, Baoan District, Shenzhen, P.R.China.

T: + 86 755 2747 1900 F: + 86 755 2749 1460 E: info@ginverter.com

Datasheet	Growatt 1000-24SL	Growatt 1000-48SL	Growatt 2000-24SL	Growatt 3000-24SL	Growatt 3000-48SL	Growatt 4000SL	Growatt 5000SL	
Rated Power	1000VA/800W	1000VA/1000W	2000VA/1600W	3000VA/2400W	3000VA/2400W	4000VA/3200W	5000VA/4000W	
<b>INPUT</b>								
Voltage	120 VAC or 230 VAC	120 VAC or 230 VAC	230 VAC	230 VAC	230 VAC	230 VAC	230 VAC	
Selectable Voltage Range	95-140 VAC or 170-280 VAC (For Personal Computers) 65-140 VAC or 90-280 VAC (For Home Appliances)		170-280 VAC (For Personal Computers) 90-280 VAC (For Home Appliances)					
Frequency Range	50 Hz/60 Hz (Auto sensing)	50 Hz/60 Hz (Auto sensing)	50 Hz/60 Hz (Auto sensing)	50 Hz/60 Hz (Auto sensing)	50 Hz/60 Hz (Auto sensing)	50 Hz/60 Hz (Auto sensing)	50 Hz/60 Hz (Auto sensing)	
<b>OUTPUT</b>								
AC Voltage Regulation (Batt. Mode)	110/120 VAC $\pm$ 5% (User selectable) or 230VAC $\pm$ 5%		230VAC $\pm$ 5%	230VAC $\pm$ 5%	230VAC $\pm$ 5%	230VAC $\pm$ 5%	230VAC $\pm$ 5%	
Surge Power	2000VA	2000VA	4000VA	6000VA	6000VA	8000VA	10000VA	
Efficiency (Peak)	90% - 93%	90% - 93%	93%	93%	93%	93%	93%	
Transfer Time	10 ms (For Personal Computers) 20 ms (For Home Appliances)							
Waveform	Pure sine wave	Pure sine wave	Pure sine wave	Pure sine wave	Pure sine wave	Pure sine wave	Pure sine wave	
<b>BATTERY &amp; AC CHARGER</b>								
Battery Voltage	24 VDC	48 VDC	24 VDC	24 VDC	48 VDC	48 VDC	48 VDC	
Floating Charge Voltage	27 VDC	54 VDC	27 VDC	27 VDC	54 VDC	54 VDC	54 VDC	
Overcharge Protection	31 VDC	62 VDC	31 VDC	31 VDC	62 VDC	60 VDC	60 VDC	
<b>SOLAR CHARGER &amp; AC CHARGER</b>								
Maximum PV Array Power	600 W	900 W	600 W	600 W	900 W	3000 W	3000 W	
MPPT Range @ Operating Voltage	30VDC – 66VDC	60VDC – 88VDC	30VDC – 66VDC	30VDC – 66VDC	60VDC – 88VDC	60VDC – 115VDC	60VDC – 115VDC	
Maximum PV Array Open Circuit Voltage	75 VDC	102 VDC	75 VDC	75 VDC	102 VDC	145 VDC	145 VDC	
Maximum Solar Charge Current	25A	18 A	25A	25A	18 A	60 A	60 A	
Maximum AC Charge Current	10 A / 20 A	10 A / 15 A	20 A or 30 A	20 A or 30 A	10 A or 15 A	60 A	60 A	
Maximum Charge Current	25A	18 A	30A	30A	18 A	120A	120A	
Maximum Efficiency	98%	98%	98%	98%	98%	98%	98%	
Standby Power Consumption	2 W	2 W	2 W	2 W	2 W	2 W	2 W	
<b>PHYSICAL</b>								
Dimension (D x W x H )mm	100 x 272 x 355	100 x 272 x 355	100 x 272 x 355	100 x 272 x 355	100 x 272 x 355	140 x 295 x 540	140 x 295 x 540	
Net Weight (kgs)	6.8	6.8	7.0	7.4	7.4	12.5	13.5	

\* There are charging current selection only available for 230VAC system.  
Product specifications are subject to change without further notice

Datasheet	Growatt 1000-24SL	Growatt 1000-48SL	Growatt 2000-24SL	Growatt 3000-24SL	Growatt 3000-48SL	Growatt 4000SL	Growatt 5000SL
Inverter Power	800W	1000W	1600W	2400W	2400W	3200W	4000W
Pmax. generated from solar charger	25Amp , 600W	20Amp , 900W	25Amp , 600W	25Amp , 600W	20Amp , 900W	60Amp , 3000W	60Amp , 3000W
Best Panel Configuration	500Wp (250Wp x 2pcs)	1000Wp (250Wp x 4pcs)	500Wp (250Wp x 2pcs)	500Wp (250Wp x 2pcs)	1500Wp (250Wp x 6pcs)	3000Wp (250Wp x 12pcs)	3000Wp (250Wp x 12pcs)